

POWER ADAPTER, MULTI-RADIO (MRPA)																									
	TAMCN: H7705																								
	ID: 10911A																								
	NSN: 6130-01-473-0349																								
Functional Description																									
<p>The Multi Radio Power Adapter (MRPA) also known as the Advanced SINCGARS Alternative Power Supply Suitcase (ASAPS-SC), is designed to power six 12V radios using 110VAC and/or 12VDC (supplied by a vehicle battery). While fully capable of operating from either a 110VAC or 12VDC power source, the MRPA is more effective when both are used together because the vehicle battery acts as an uninterruptible power supply (UPS) for your radios. The AC power source not only provides power to operate the SINCGARS radios but also charges the vehicle battery. The portable suitcase-sized MRPA comes with six 12-foot power cords that allow up to six radios to be spread out up to 12 feet away.</p>																									
Technical Description																									
<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;"><u>Adapter Set</u></td> <td style="width: 50%;"><u>Dimensions</u></td> </tr> <tr> <td>Manufacturer: PulseTech</td> <td>Length (in): 16.25</td> </tr> <tr> <td>Model: ASAPS-SC</td> <td>Width (in): 19.75</td> </tr> <tr> <td>740X809</td> <td>Height (in): 11</td> </tr> <tr> <td><u>Power</u></td> <td>Weight (lbs): 33</td> </tr> <tr> <td>Input: 12 VDC 110 VAC</td> <td>Volume (ft³): 2</td> </tr> <tr> <td>Output: 13.5 VDC</td> <td></td> </tr> <tr> <td>Frequency (Hz): 40-70</td> <td></td> </tr> <tr> <td><u>Warranty</u></td> <td>1 Year</td> </tr> <tr> <td colspan="2"><u>Specifications</u></td> </tr> <tr> <td colspan="2">Handles Input AC Power input from 92-135VAC.</td> </tr> <tr> <td colspan="2">Output Amperage: Demand Based, Up To 5 Amps Per Channel.</td> </tr> </table>		<u>Adapter Set</u>	<u>Dimensions</u>	Manufacturer: PulseTech	Length (in): 16.25	Model: ASAPS-SC	Width (in): 19.75	740X809	Height (in): 11	<u>Power</u>	Weight (lbs): 33	Input: 12 VDC 110 VAC	Volume (ft ³): 2	Output: 13.5 VDC		Frequency (Hz): 40-70		<u>Warranty</u>	1 Year	<u>Specifications</u>		Handles Input AC Power input from 92-135VAC.		Output Amperage: Demand Based, Up To 5 Amps Per Channel.	
<u>Adapter Set</u>	<u>Dimensions</u>																								
Manufacturer: PulseTech	Length (in): 16.25																								
Model: ASAPS-SC	Width (in): 19.75																								
740X809	Height (in): 11																								
<u>Power</u>	Weight (lbs): 33																								
Input: 12 VDC 110 VAC	Volume (ft ³): 2																								
Output: 13.5 VDC																									
Frequency (Hz): 40-70																									
<u>Warranty</u>	1 Year																								
<u>Specifications</u>																									
Handles Input AC Power input from 92-135VAC.																									
Output Amperage: Demand Based, Up To 5 Amps Per Channel.																									
<p>NOTES: The MRPA is being replaced by the 24 Volt Multi-Radio Power Adapter Tower. NSN: 5935-01-578-7684.</p>																									